

Design and modeling of asymmetric bow-tie VCSELs for 100 GHz and beyond

Original

Design and modeling of asymmetric bow-tie VCSELs for 100 GHz and beyond / Dalessandro, Martino.; Torrelli, V.; Gullino, Alberto; Alasio, M. G. C.; Nespola, A.; Romero García, S.; Debernardi, Pierluigi. - In: OPTICS EXPRESS. - ISSN 1094-4087. - 34:5(2026), pp. 7979-7995. [10.1364/oe.578425]

Availability:

This version is available at: 11583/3008347 since: 2026-03-07T09:03:11Z

Publisher:

Optica Publishing Group

Published

DOI:10.1364/oe.578425

Terms of use:

This article is made available under terms and conditions as specified in the corresponding bibliographic description in the repository

Publisher copyright

(Article begins on next page)

Design and modeling of asymmetric bow-tie VCSELs for 100 GHz and beyond: supplement

M. D'ALESSANDRO,^{1,2}  V. TORRELLI,^{1,2,*}  A. GULLINO,²  M. G. C. ALASIO,^{1,2}  A. NESPOLA,³  S. ROMERO GARCÍA,⁴  AND P. DEBERNARDI²

¹*Department of Electronics and Telecommunications (DET), Politecnico di Torino, Corso Duca degli Abruzzi, 24, 10129, Torino, Italy*

²*Istituto di Elettronica e di Ingegneria dell'Informazione e delle Telecomunicazioni (IEIIT) del Consiglio Nazionale delle Ricerche (CNR), Corso Duca degli Abruzzi, 24, 10129, Torino, Italy*

³*LINKS Foundation, Via Pier Carlo Boggio, 61, 10138 Torino, Italy*

⁴*Cisco Optical, Nuremberg, Germany*

*valerio.torrelli@polito.it

This supplement published with Optica Publishing Group on 26 February 2026 by The Authors under the terms of the [Creative Commons Attribution 4.0 License](https://creativecommons.org/licenses/by/4.0/) in the format provided by the authors and unedited. Further distribution of this work must maintain attribution to the author(s) and the published article's title, journal citation, and DOI.

Supplement DOI: <https://doi.org/10.6084/m9.figshare.30462467>

Parent Article DOI: <https://doi.org/10.1364/OE.578425>

Design and modelling of asymmetric bow-tie VCSELs for 100 GHz and beyond

In this supplementary material, we report the proof Eq. (5), which allows for the calculation of the output optical power as a post processing of the time-varying expansion coefficients.

1. CALCULATION OF THE OUTPUT POWER

After solving the dynamical equations (3)-(4), we must calculate the output optical power $P(t)$ emitted by the VCSEL. To this aim, a few preliminary calculations are needed. Let us begin by defining:

$$k_{ij}^{(0)} = \frac{k_{ij}}{1 + i\alpha_H} \quad (\text{S1})$$

and

$$k'_{ij} = \Re\{k_{ij}\}. \quad (\text{S2})$$

As discussed in [1], the modulation bandwidth enhancement in BT-VCSEL comes from two modes interacting to generate a PPR peak, so let us fix $M = 2$ for simplicity.

Identifying the second term of the right-hand side of (4) as the stimulated recombination term,

$$R_{\text{st}}(x, y, t) = v_g \Re\{\tilde{g}(x, y, t)\} S(x, y, t), \quad (\text{S3})$$

let us evaluate its volume integral, as it represents the whole power generated by carriers inside the VCSEL. For carriers, integrating along the longitudinal direction simply implies the multiplication by the AR thickness. Expliciting S according to (10) one obtains (for simplicity, time and space dependencies are implied):

$$\begin{aligned} \iiint_{\mathbb{R}^3} R_{\text{st}} dx dy dz &= N_{\text{QW}} d_{\text{QW}} \iint_{\mathbb{R}^2} R_{\text{st}} dx dy = \\ &= N_{\text{QW}} d_{\text{QW}} v_g \iint_{\mathbb{R}^2} \frac{g(N)}{1 + \epsilon_{\text{nl}} g} \left(|e_1|^2 |\Psi_1|^2 + |e_2|^2 |\Psi_2|^2 + 2\Re\{e_1^* e_2 \Psi_1^* \Psi_2\} \right) dx dy = \\ &\stackrel{\text{Eq. (8)}-\text{Eq. (S1)}-\text{Eq. (S2)}}{=} \frac{2N_{\text{QW}} d_{\text{QW}}}{\Gamma_z} \left(k'_{11} |e_1|^2 + k'_{22} |e_2|^2 + 2\Re\{k_{12}^{(0)} e_1^* e_2\} \right). \end{aligned} \quad (\text{S4})$$

Consider now:

$$\begin{aligned} \frac{d|e_1|^2}{dt} &= \frac{de_1}{dt} e_1^* + e_1 \left(\frac{de_1}{dt} \right)^* = 2\Re\left\{ \frac{de_1}{dt} e_1^* \right\} = \\ &\stackrel{\text{Eq. (3)}}{=} -2\alpha_1 |e_1|^2 + 2k'_{11} |e_1|^2 + 2\Re\{k_{12} e_1^* e_2\}. \end{aligned} \quad (\text{S5})$$

Following the same procedure:

$$\frac{d|e_2|^2}{dt} = -2\alpha_2 |e_2|^2 + 2k'_{22} |e_2|^2 + 2\Re\{k_{21} e_1 e_2^*\}. \quad (\text{S6})$$

Finally, we can express the output power as a power balance. Specifically, the net total power inside the VCSEL can be obtained as:

$$P_{\text{net}} = E_{\text{ph}} \iiint_{\mathbb{R}^3} \frac{\partial S}{\partial t} dx dy dz, \quad (\text{S7})$$

where E_{ph} is the photon energy at our reference wavelength. Note that integrating photons over the longitudinal dimension produces a multiplication by the optical length $L_{\text{opt}} = N_{\text{QW}} d_{\text{QW}} / \Gamma_z$. Substituting Eq. (10) with $M = 2$ in Eq. (S7) allows to identify the terms associated to generation and the ones related to escape. The latter are used to calculate the output power. Equation Eq. (S7) becomes:

$$P_{\text{net}} \stackrel{\text{Eq. (10)}}{=} E_{\text{ph}} L_{\text{opt}} \iint_{\mathbb{R}^2} \frac{d}{dt} \left(|e_1|^2 |\Psi_1|^2 + |e_2|^2 |\Psi_2|^2 + 2\Re\{e_1^* e_2 \Psi_1^* \Psi_2\} \right) dx dy. \quad (\text{S8})$$

By recalling Eq. (S5)–Eq. (S6) and assuming modes normalization in the QW section, one can further define:

$$\xi_{12} = \iint_{\mathbb{R}^2} \Psi_1^* \Psi_2 \, dx dy, \quad (\text{S9})$$

so that it is possible to write:

$$P_{\text{net}} = E_{\text{ph}} L_{\text{opt}} \left[-2\alpha_1 |e_1|^2 + 2k'_{11} |e_1|^2 + 2\Re \{k_{12} e_1^* e_2\} + \right. \\ \left. -2\alpha_2 |e_2|^2 + 2k'_{22} |e_2|^2 + 2\Re \{k_{21} e_1 e_2^*\} + 2\Re \left\{ \frac{d(e_1^* e_2)}{dt} \xi_{12} \right\} \right]. \quad (\text{S10})$$

Let us further develop the following two terms:

$$2\Re \{k_{12} e_1^* e_2 + k_{21} e_1 e_2^*\} = 2\Re \left\{ (1 + i\alpha_H) \left(k_{12}^{(0)} e_1^* e_2 + k_{21}^{(0)} e_1 e_2^* \right) \right\}. \quad (\text{S11})$$

However, from Eq. (8), one can notice that $k_{12}^{(0)} = \left(k_{21}^{(0)} \right)^*$, so that:

$$2\Re \{k_{12} e_1^* e_2 + k_{21} e_1 e_2^*\} = 4\Re \left\{ k_{12}^{(0)} e_1^* e_2 \right\}, \quad (\text{S12})$$

being independent on α_H . Recalling Eq. (S4) and the definition of L_{opt} , the total optical power can be rewritten as:

$$P_{\text{net}} = E_{\text{ph}} \iiint_{\mathbb{R}^3} R_{\text{st}} \, dx dy dz - 2E_{\text{ph}} L_{\text{opt}} \left[\alpha_1 |e_1|^2 + \alpha_2 |e_2|^2 - \Re \left\{ \frac{d(e_1^* e_2)}{dt} \xi_{12} \right\} \right], \quad (\text{S13})$$

where the first term is the generated power, while the second one is the output power. The final formula for $P(t)$ also accounts for the modal outcoupling efficiencies η_1, η_2 , which are phenomenologically added to the expansion coefficients [2] as:

$$P(t) = 2E_{\text{ph}} L_{\text{opt}} \left\{ \eta_1 \alpha_1 |e_1(t)|^2 + \eta_2 \alpha_2 |e_2(t)|^2 - \sqrt{\eta_1 \eta_2} \Re \left\{ \frac{d[e_1^*(t) e_2(t)]}{dt} \xi_{12} \right\} \right\}. \quad (\text{S14})$$

The last term represents a cross power, which is zero under stationary conditions ($d/dt = 0$) or for orthogonal modes ($\xi_{12} = 0$).

REFERENCES

1. M. D'Alessandro, V. Torrelli, F. Bertazzi, *et al.*, "Transverse coupled cavity vcsels: Bridging ultrabroadband dynamics to optical supermodes," *IEEE Photonics J.* **16**, 1–7 (2024).
2. L. A. Coldren and S. W. Corzine, *Diode Lasers and Photonic Integrated Circuits* (John Wiley & Sons, New York, 1995).