POLITECNICO DI TORINO Repository ISTITUZIONALE

Update: On the synthesis of quantum Hall array resistance standards (2015 Metrologia 52 31)

Original

Update: On the synthesis of quantum Hall array resistance standards (2015 Metrologia 52 31) / Ortolano, Massimo; Callegaro, Luca. - In: METROLOGIA. - ISSN 0026-1394. - 56:2(2019), p. 022101. [10.1088/1681-7575/ab065f]

Availability:

This version is available at: 11583/2726851 since: 2019-03-01T11:54:29Z

Publisher:

IOP

Published

DOI:10.1088/1681-7575/ab065f

Terms of use:

This article is made available under terms and conditions as specified in the corresponding bibliographic description in the repository

Publisher copyright

IOP postprint/Author's Accepted Manuscript

"This is the accepted manuscript version of an article accepted for publication in METROLOGIA. IOP Publishing Ltd is not responsible for any errors or omissions in this version of the manuscript or any version derived from it. The Version of Record is available online at http://dx.doi.org/10.1088/1681-7575/ab065f

(Article begins on next page)

Update: On the synthesis of quantum Hall array resistance standards (2015 Metrologia 52 31)

Massimo Ortolano^{1,2} and Luca Callegaro²,

¹ Dipartimento di Elettronica e Telecomunicazioni, Politecnico di Torino

Corso Duca degli Abruzzi 24, 10129 Torino, Italy ²INRIM - Istituto Nazionale di Ricerca Metrologica Strada delle Cacce, 91 - 10135 Torino, Italy

E-mail: massimo.ortolano@polito.it

Abstract. This work provides an update, according to the revised SI, to table 1 of M. Ortolano et al., "On the synthesis of quantum Hall array resistance standards", *Metrologia*, 52, p. 31–39, 2015. The table reports fractions of the quantized Hall resistance approximating decadic values and the associated deviations. In several cases, the deviations have become smaller in the revised SI.

Submitted to: Metrologia

Quantum Hall array resistance standards (QHARS) are integrated circuits of interconnected quantum Hall elements. They are designed to provide a quantized resistance R approximating a nominal resistance value R_0 of practical interest, typically a decadic value (e.g., $10\,\mathrm{k}\Omega$). R is a fraction $R=(p/q)R_\mathrm{H}$ of the quantized Hall resistance R_H of the individual elements composing the QHARS, and p and q are integers. The quantized Hall resistance is a submultiple of the von Klitzing constant, $R_\mathrm{H}=R_\mathrm{K}/i,i$ being a small integer (here we assume i=2, as is usually the case).

In [1], we proposed an algorithm that, given the target resistance R_0 , allows to calculate the fractions p/q of interest, and to design the corresponding QHARS networks. Table 1 of [1] provides several examples of practical interest for the decadic values $100\,\Omega$, $1\,\mathrm{k}\Omega$, $10\,\mathrm{k}\Omega$, $100\,\mathrm{k}\Omega$ and $1\,\mathrm{M}\Omega$. The approximations reported in [1], and the corresponding deviations of R from R_0 , were calculated by assuming the conventional value of the von Klitzing constant $R_{\mathrm{K-90}} = 25\,812.807\,\Omega$ [2, Appendix 1].

The redefinition of the International System of Units [3] fixes the value of the von Klitzing constant $R_{\rm K}$ according to the last CODATA 2017 recommendation [4, table 3], $R_{\rm K}=h/e^2=25\,812.807\,459\,304\,5\,\Omega$ (calculated to 15 significant figures, as given in [5]). This value relatively differs from $R_{\rm K-90}$ by 1.78×10^{-8} .

The present work provides in table 1 below an update to table 1 of [1] according to the revised SI. A few sign errors in the original δ_{90} values have also been corrected. It is of interest that several approximations provide a lower relative error in the revised SI.

The Mathematica [6] notebook implementing the search of approximating fractions as described in [1] and employed to generate table 1 is available at https://github.com/INRIMQuantumElectricalMetrology/SternBrocot.

References

- M. Ortolano, M. Abrate, and L. Callegaro, "On the synthesis of quantum Hall array resistance standards," *Metrologia*, vol. 52, p. 31, 2015. [Online]. Available: https://doi.org/10.1088/0026-1394/52/1/31
- [2] Bureau International des Poids et Mesures, "The International System of Units (SI)," 2006, 8th edition. [Online]. Available: www.bipm.org
- [3] —, "Draft of the 9th SI brochure," Feb. 2018. [Online]. Available: www.bipm.org

Table 1. Summary of the cases analyzed in [1]: $\rho_{0-90} = R_0/R_{\text{H-90}}$ is the target resistance value normalized to the Hall resistance $R_{\text{H-90}} = R_{\text{K-90}}/2$; $\rho_0 = R_0/R_{\text{H}}$ is the target resistance value normalized to the Hall resistance $R_{\text{H}} = R_{\text{K}}/2$, calculated with the revised value of R_{K} ; $\rho = p/q$ is a rational approximation for ρ_0 and ρ_{0-90} ; $\delta_{90} = (\rho - \rho_{0-90})/\rho_{0-90}$ and $\delta = (\rho - \rho_0)/\rho_0$ are the relative errors of the approximation. Values are rounded at the 10^{-10} level. Table 1 of [1] reported δ_{90} .

ρ	δ_{90}	δ
$R_0 = 100 \Omega$		
47/6066	$+1.5900 \times 10^{-6}$	$+1.6078 \times 10^{-6}$
78/10067	-5.235×10^{-7}	-5.057×10^{-7}
125/16133	$+2.712 \times 10^{-7}$	$+2.890 \times 10^{-7}$
203/26200	-3.42×10^{-8}	-1.64×10^{-8}
$R_0 = 1 \mathrm{k}\Omega$		
203/2620	-3.42×10^{-8}	-1.64×10^{-8}
235/3033	$+1.5900 \times 10^{-6}$	$+1.6078 \times 10^{-6}$
	$R_0 = 10 \mathrm{k}\Omega$	
203/262	-3.42×10^{-8}	-1.64×10^{-8}
	$R_0 = 100 \mathrm{k}\Omega$	
1015/131	-3.42×10^{-8}	-1.64×10^{-8}
$R_0 = 1 \mathrm{M}\Omega$		
4029/52	-1.9288×10^{-6}	-1.9110×10^{-6}
6121/79	$+1.2130 \times 10^{-6}$	$+1.2307 \times 10^{-6}$
10150/131	-3.42×10^{-8}	-1.64×10^{-8}

- [4] D. B. Newell, F. Cabiati, J. Fischer, K. Fujii, S. G. Karshenboim, H. S. Margolis, E. de Mirandés, P. J. Mohr, F. Nez, K. Pachucki, T. J. Quinn, B. N. Taylor, M. Wang, B. M. Wood, and Z. Zhang, "The CODATA 2017 values of h, e, k, and N_A for the revision of the SI," Metrologia, vol. 55, p. L13, 2018. [Online]. Available: http://stacks.iop.org/0026-1394/55/i=1/a=L13
- [5] Consultative Committee for Electricity and Magnetism, "Mise en pratique for the definition of the ampere and other electric units in the SI," Dec. 2017, draft for Appendix 2 of the SI Brochure for the "Revised SI". [Online]. Available: www.bipm.org
- [6] Wolfram, "Mathematica 11." [Online]. Available: http://www.wolfram.com/mathematica/